

# An algorithm for the calculation of the minimal polynomial

 S. BIAŁAS<sup>1\*</sup> and M. BIAŁAS<sup>2</sup>
<sup>1</sup> The School of Banking and Management, 4 Armii Krajowej St., 30-150 Kraków, Poland

<sup>2</sup> Faculty of Management, AGH University of Science and Technology, 30 Mickiewicza St., 30-059 Kraków, Poland

**Abstract.** This paper gives the simple algorithm for calculation of the degree and coefficients of the minimal polynomial for the complex matrix  $A = [a_{ij}]_{n \times n}$ .

**Key words:** matrix, minimal polynomial, characteristic polynomial.

## 1. Introduction

We use the standard notation. We denote by  $M_{m,n}$  the set of  $m \times n$  real or complex matrices. In case  $n = m$  we will write  $M_n$  instead of  $M_{n,n}$ .

A complex polynomial  $f(\lambda)$  is called an annihilation polynomial for a matrix  $A \in M_n$  if  $f(\lambda) \neq 0$  and  $f(A) = 0 \in M_n$ . The complex polynomial

$$f(\lambda) = a_n \lambda^n + a_{n-1} \lambda^{n-1} + \dots + a_1 \lambda + a_0,$$

where  $a_n \neq 0$ , is called monic if its leading coefficient  $a_n = 1$ . The monic polynomial  $\psi(\lambda)$  of least degree for which  $\psi(A) = 0 \in M_n$  is called the minimal polynomial of the matrix  $A \in M_n$ .

The properties and the applications of the minimal polynomials in the control theory have been presented in [1, 2].

In this paper the simple algorithm is given for the calculation of the degree and coefficients of the minimal polynomial.

For the matrix  $A = [a_{ij}] \in M_n$  we will use the following notations:

$\varphi(\lambda) = \det(\lambda I - A)$  – characteristic polynomial of the matrix  $A$ ,

$\psi(\lambda)$  – minimal polynomial of the matrix  $A$ ,

$\text{vec} A = [a_{11} \ a_{12} \ \dots \ a_{1n} \ a_{21} \ a_{22} \ \dots \ a_{2n} \ \dots \ a_{n1} \ a_{n2} \ \dots \ a_{nn}]^T$ ,

$A^0 = I \in M_n$ ,

$A^k = A^{k-1} A \quad (k = 1, 2, \dots)$ , (1)

$A^k = [a_{ij}^{(k)}] \quad (k = 0, 1, 2, \dots)$ ,

$a^{(k)} = \text{vec} A^k \quad (k = 0, 1, 2, \dots)$ ,

$B_k = [a^{(0)} a^{(1)} \ \dots \ a^{(k)}] \quad (k = 0, 1, 2, \dots)$

where  $a^{(k)}$  is  $k+1$ -th column of the matrix  $B_k \in M_{n^2, k+1}$ ,

$\text{rank}(B)$  – rank of the matrix  $B$ ,

$N = \{1, 2, 3, \dots\}$ ,

$I$  or  $I_n$  – unit matrix,

$\text{deg} f(x)$  – degree of the polynomial  $f(\lambda)$ ,

$\emptyset$  – empty set.

**Example 1.** For the matrix  $A = \begin{bmatrix} a_{11} & a_{12} \\ a_{21} & a_{22} \end{bmatrix}$  we have:

$$\begin{aligned} a^{(0)} &= [1 \ 0 \ 0 \ 1]^T, \quad a^{(1)} = [a_{11} \ a_{12} \ a_{21} \ a_{22}]^T, \dots, \\ a^{(k)} &= [a_{11}^{(k)} \ a_{12}^{(k)} \ a_{21}^{(k)} \ a_{22}^{(k)}]^T, \quad B_0 = [a^{(0)}] = [1 \ 0 \ 0 \ 1]^T, \\ B_1 &= [a^{(0)} a^{(1)}] = \begin{bmatrix} 1 & a_{11} \\ 0 & a_{12} \\ 0 & a_{21} \\ 1 & a_{22} \end{bmatrix}. \end{aligned}$$

## 2. An algorithm for the calculation of the degree and the coefficients of the minimal polynomial

For the matrix  $A = [a_{ij}] \in M_n$  we will prove the following Lemma.

**Lemma 1.** If the matrix  $A = [a_{ij}] \in M_n$ , the matrix  $B_k$  is defined by (1), then

$$K = \{k \in N : \text{rank } B_k = \text{rank } B_{k-1}\} \neq \emptyset \quad \text{and} \quad n \in K.$$

**Proof.** We see that if

$$\varphi(\lambda) = \det(\lambda I - A) = \lambda^n + b_{n-1} \lambda^{n-1} + \dots + b_1 \lambda + b_0,$$

then

$$A^n + b_{n-1} A^{n-1} + \dots + b_1 A + b_0 I = 0 \in M_n,$$

$$a^{(n)} = -[b_{n-1} a^{(n-1)} + \dots + b_1 a^{(1)} + b_0 a^{(0)}],$$

$$\text{rank } B_n = \text{rank} [a^{(0)} a^{(1)} \ \dots \ a^{(n)}]$$

$$= \text{rank} [a^{(0)} a^{(1)} \ \dots \ a^{(n-1)} 0] = \text{rank } B_{n-1},$$

where  $0 = [0 \ 0 \ \dots \ 0]^T \in M_{n^2, 1}$ . Therefore  $n \in K$  and  $K \neq \emptyset$ .

**Definition 1.** A number  $k_0 = \min K$  is called the associated rank of the matrix  $A = [a_{ij}] \in M_n$ .

**Theorem 1.** If  $k_0$  is the associated rank of the matrix  $A = [a_{ij}] \in M_n$  and  $\psi(\lambda)$  is the minimal polynomial of this matrix then:

\*e-mail: sbialas@uci.agh.edu.pl

- 1)  $\text{rank } B_k = k + 1 \quad (k = 0, 1, \dots, k_0 - 1)$ ,
- 2)  $\text{rank } B_k = k_0 \quad (k \geq k_0)$ ,
- 3)  $\text{deg } \psi(\lambda) = k_0$ ,

where the matrix  $B_k$  is defined by the relation (1).

**Proof.** Let  $B_k = [a^{(0)} a^{(1)} \dots a^{(k_0-1)} a^{(k_0)} a^{(k_0+1)} \dots a^{(k)}]$ .

First we will prove that  $\text{rank} B_k = k + 1 \quad (k = 0, 1, \dots, k_0 - 1)$ . From the definition of  $k_0$  it follows that  $\text{rank} B_{k_0} = \text{rank} B_{k_0-1}$ . For  $k_0 = 1$   $\text{rank} B_1 = \text{rank} B_0 = 1$ .

However, for  $k_0 > 1$  we have:

$$\text{rank} B_1 > \text{rank} B_0 = 1 \Rightarrow \text{rank} B_1 = 2,$$

$$\text{rank} B_2 > \text{rank} B_1 = 2 \Rightarrow \text{rank} B_2 = 3,$$

.....

$$\text{rank} B_{k_0-1} > \text{rank} B_{k_0-2} = k_0 - 1 \Rightarrow \text{rank} B_{k_0-1} = k_0.$$

Therefore  $\text{rank} B_k = k + 1$  for  $k \in \{0, 1, 2, \dots, k_0 - 1\}$  and  $\text{rank} B_{k_0} = \text{rank} B_{k_0-1} = k_0$ . Hence it follows that the columns  $a^{(0)}, a^{(1)}, \dots, a^{(k_0-1)}$  are linear independent and the column  $a^{(k_0)}$  can be written as the linear combination of the columns  $a^{(0)}, a^{(1)}, \dots, a^{(k_0-1)}$ , so there exists  $\alpha = (\alpha_0, \alpha_1, \dots, \alpha_{k_0-1}) \in C^{k_0}$  such that

$$\alpha_0 a^{(0)} + \alpha_1 a^{(1)} + \dots + \alpha_{k_0-1} a^{(k_0-1)} = -a^{(k_0)}.$$

It denotes that

$$\alpha_0 I + \alpha_1 A + \dots + \alpha_{k_0-1} A^{k_0-1} + A^{k_0} = 0 \in M_n$$

and the polynomial  $f(\lambda) = \alpha_0 + \alpha_1 \lambda + \dots + \lambda^{k_0}$  is the annihilatory polynomial of the matrix  $A$ .

For  $k > k_0$ ,  $m = k - k_0$  and any arbitrary numbers  $\beta_0, \beta_1, \dots, \beta_{m-1} \in C$  the polynomial  $g(\lambda) = f(\lambda)(\beta_0 + \beta_1 \lambda + \dots + \beta_{m-1} \lambda^{m-1} + \lambda^m) = \gamma_0 + \gamma_1 \lambda + \dots + \gamma_{k-1} \lambda^{k-1} + \lambda^k$  is the annihilatory polynomial of the matrix  $A$ , too.

Therefore

$$\gamma_0 I + \gamma_1 A + \dots + \gamma_{k-1} A^{k-1} + A^k = 0 \in M_n,$$

$$\gamma_0 a^{(0)} + \gamma_1 a^{(1)} + \dots + \gamma_{k-1} a^{(k-1)} + a^{(k)} = 0 \in M_{n^2, 1}. \tag{2}$$

In the matrix  $B_k = [a^{(0)} a^{(1)} \dots a^{(k_0-1)} a^{(k_0)} a^{(k_0+1)} \dots a^{(k)}]$  the column  $a^{(j)}$  can be multiplied by  $-\gamma_j \quad (j = 0, 1, \dots, k-1)$  and added to the column  $a^{(k)}$ . Hence and (2) we have

$$\text{rank} B_k = \text{rank} [a^{(0)} a^{(1)} \dots a^{(k-1)} 0] = \text{rank} B_{k-1}.$$

Similar transformation can be used to the matrix  $B_{k-1}$ . At the end, we have

$$\begin{aligned} \text{rank} B_k &= \text{rank} [a^{(0)} a^{(1)} \dots a^{(k_0-1)} a^{(k_0)} 0 \dots 0] \\ &= \text{rank} B_{k_0} = k_0 \end{aligned}$$

for  $k \geq k_0$ . This finishes the proof of 2) of the Theorem 1.

Now we prove that if  $\psi(\lambda)$  is the minimal polynomial of the matrix  $A$  then  $\text{deg } \psi(\lambda) = k_0$ .

Hence that  $\text{rank} B_{k_0} = \text{rank} B_{k_0-1} = k_0$  it follows that the set of equations

$$B_{k_0-1} \alpha = -a^{(k_0)},$$

with the unknown  $\alpha = [\alpha_0 \alpha_1 \dots \alpha_{k_0-1}]^T \in C^{k_0}$ , has only one solution and

$$\alpha_0 I + \alpha_1 A + \dots + \alpha_{k_0-1} A^{k_0-1} + A^{k_0} = 0 \in M_n,$$

besides

$$\alpha_0 + \alpha_1 \lambda + \dots + \alpha_{k_0-1} \lambda^{k_0-1} + \lambda^{k_0}, \tag{3}$$

is the annihilatory polynomial of the matrix  $A$ .

Hence that  $\text{rank} B_k = k + 1 \quad (k = 0, 1, \dots, k_0 - 1)$  it follows that the set of equations

$$B_{k-1} \alpha = -a^{(k)},$$

with the unknown  $\alpha = [\alpha_0 \alpha_1 \dots \alpha_{k-1}]^T \in C^k$ , has not the solutions.

This denotes that the polynomial (3) is the minimal polynomial of the matrix  $A$  and  $\text{deg } \psi(\lambda) = k_0$ .

Now, we give the algorithm for the calculation of the degree and coefficients of the minimal polynomial of the matrix  $A = [a_{ij}] \in M_n$ .

Consider the matrix

$$B_n = [a^{(0)} a^{(1)} \dots a^{(n)}] \in M_{n^2, n+1},$$

which is defined in (1).

The elements of the matrix  $B_n$  are denoted by  $b_{ij}$ , therefore  $B_n = [b_{ij}] \in M_{n^2, n+1}$ , where  $b_{11} = 1, b_{12} = a_{11}^{(1)}, \dots, b_{1, n+1} = a_{11}^{(n)}, \dots, b_{n^2, n+1} = a_{nn}^{(n)}$ .

We will calculate the rank of the matrix  $B_n$  by Gaussian elimination, except interchange and cancel of the null columns.

We obtain

$$\text{rank} B_n = \text{rank} \begin{bmatrix} 1 & b_{12} & \dots & b_{1, n+1} \\ 0 & b_{22}^{(1)} & \dots & b_{2, n+1}^{(1)} \\ 0 & b_{32}^{(1)} & \dots & b_{3, n+1}^{(1)} \\ \dots & \dots & \dots & \dots \\ 0 & b_{n^2, 2}^{(1)} & \dots & b_{n^2, n+1}^{(1)} \end{bmatrix},$$

where, for example  $b_{22}^{(1)} = b_{22}, \dots, b_{2, n+1}^{(1)} = b_{2, n+1}, b_{n^2, 2}^{(1)} = b_{n^2, 2} - b_{12}$ .

From the Lemma 1 it follows that  $n \in K = \{k \in N : \text{rank} B_k = \text{rank} B_{k-1}\}$ .

An algorithm for the calculation of the minimal polynomial

Therefore there exists  $r \in N$  such that  $r \leq n$  and

$$\text{rank}B_n = \text{rank} \begin{bmatrix} 1 & b_{12} & b_{13} & \dots & \dots & \dots & \dots & \dots & \dots & \dots & b_{1,n+1} \\ 0 & b_{12}^{(1)} & b_{23}^{(1)} & \dots & \dots & \dots & \dots & \dots & \dots & \dots & b_{2,n+1}^{(1)} \\ 0 & 0 & b_{33}^{(2)} & \dots & \dots & \dots & \dots & \dots & \dots & \dots & b_{3,n+1}^{(2)} \\ \dots & \dots & \dots & \dots & \dots & \dots & \dots & \dots & \dots & \dots & \dots \\ 0 & 0 & 0 & \dots & 0 & b_{rr}^{(r-1)} & b_{r,r+1}^{(r-1)} & \dots & \dots & \dots & b_{r,n+1}^{(r-1)} \\ 0 & 0 & 0 & \dots & 0 & 0 & 0 & b_{r+1,r+2}^{(r-1)} & \dots & \dots & b_{r+1,n+1}^{(r-1)} \\ 0 & 0 & 0 & \dots & 0 & 0 & 0 & b_{r+2,r+2}^{(r-1)} & \dots & \dots & b_{r+2,n+1}^{(r-1)} \\ \dots & \dots & \dots & \dots & \dots & \dots & \dots & \dots & \dots & \dots & \dots \\ 0 & 0 & 0 & \dots & 0 & 0 & 0 & b_{n^2,r+2}^{(r-1)} & \dots & \dots & b_{n^2,n+1}^{(r-1)} \end{bmatrix},$$

where  $b_{ii}^{(i-1)} \neq 0$  ( $i = 1, 2, \dots, r$ ).

From this it follows that  $\text{rank}B_j = j$  ( $j = 1, 2, \dots, n$ ),  $\text{rank}B_{r-1} = r$ ,  $\text{rank}B_r = r$ .

Therefore  $k_0 = \min K = r$  and  $\deg \psi(\lambda) = r = k_0$ .

Thus, by Gaussian elimination we can compute the degree of the minimal polynomial of the matrix  $A$ .

Hence that  $\det B_{r-1} = \det B_{k_0-1} \neq 0$  and  $\text{rank}B_{k_0} = \text{rank}B_{k_0-1} = k_0$  it follows that the set of equations

$$B_{k_0-1}\alpha = -a^{(k_0)}, \tag{4}$$

with the unknown  $\alpha = [\alpha_0 \alpha_1 \dots \alpha_{k_0-1}]^T \in C^{k_0}$ , has only one solution and

$$\alpha_0 + \alpha_1 A + \dots + \alpha_{k_0-1} A^{k_0-1} + A^{k_0} = 0 \in M_n.$$

Therefore  $\alpha_0, \alpha_1, \dots, \alpha_{k_0-1}, 1$  are the coefficients of the minimal polynomial of the matrix  $A$ . The set of Eq. (4) is equivalent to the set of equations

$$\tilde{B}\alpha = \tilde{b},$$

where

$$\tilde{B} = \begin{bmatrix} 1 & b_{11} & \dots & \dots & b_{1r} \\ 0 & b_{22}^{(1)} & \dots & \dots & b_{2r}^{(1)} \\ 0 & 0 & b_{33}^{(2)} & \dots & b_{3r}^{(2)} \\ \dots & \dots & \dots & \dots & \dots \\ 0 & 0 & \dots & 0 & b_{rr}^{(r-1)} \end{bmatrix}, \tilde{b} = \begin{bmatrix} b_{1,r+1} \\ b_{2,r+1}^{(1)} \\ \vdots \\ b_{r,r+1}^{(r-1)} \end{bmatrix},$$

$$\alpha = [\alpha_0 \alpha_1 \dots \alpha_{k_0-1}]^T, r = k_0.$$

**Example 2.** We will calculate the minimal polynomial of the matrix

$$A = \begin{bmatrix} 3 & -3 & 2 \\ -1 & 5 & -2 \\ -1 & 3 & 0 \end{bmatrix}.$$

In this example we have

$$A^2 = \begin{bmatrix} 10 & -18 & 12 \\ -6 & 22 & -12 \\ -6 & 18 & -8 \end{bmatrix},$$

$$A^3 = \begin{bmatrix} 36 & -84 & 56 \\ -28 & 92 & -56 \\ -28 & 84 & -48 \end{bmatrix},$$

$$\text{rank}B_3 = \text{rank} \begin{bmatrix} 1 & 3 & 10 & 36 \\ 0 & -3 & -18 & -84 \\ 0 & 2 & 12 & 56 \\ 0 & -1 & -6 & -28 \\ 1 & 5 & 22 & 92 \\ 0 & -2 & -12 & -56 \\ 0 & -1 & -6 & -28 \\ 0 & 3 & 18 & 84 \\ 1 & 0 & -8 & -48 \end{bmatrix}$$

$$= \text{rank} \begin{bmatrix} 1 & 3 & 10 & 36 \\ 0 & -3 & -18 & -84 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \end{bmatrix} = 2,$$

$$\tilde{B} = \begin{bmatrix} 1 & 3 \\ 0 & -3 \end{bmatrix}, \tilde{b} = \begin{bmatrix} -10 \\ 18 \end{bmatrix}, k_0 = 2,$$

$$\alpha = [\alpha_0 \alpha_1]^T = [8 \ -6]^T.$$

Therefore,  $\psi(\lambda) = \lambda^2 - 6\lambda + 8$ . is the minimal polynomial of the matrix  $A$ .

REFERENCES

[1] S. Barnett, *Matrices in Control Theory*, Van Nostrand Reinhold Company, London, 1960.  
 [2] T. Kaczorek, *Vectors and Matrices in Automatics and Electrotechnics*, WNT, Warszawa, 1998.